

Furnizor: **Sc Trivolt Distribution SRL**  
Reg. com.: J23/3300/2016  
CIF: RO36421140  
Adresa: Strada Apusului nr 3 ( primul  
sens giratoriu Tehodor Pallady-  
Autostrada Soarelui), Catelu, Ilfov  
Banca: BRD  
IBAN: RO34BRDE441SV13182234410



**LEGRAND LAMPA DE EMERGENTA B65 - AUTOTEST/ADDRESS  
MAINT./NON MAINT. - 100 LM - 3H - LED**

**Caracteristici tehnice**

Autotest and addressable luminaires - Maintained/Non-maintained (M/NM)

Autotest/addressable luminaires incorporate an automatic self-testing system in order to check emergency lighting

Tests result is visible on 2 signalling LEDs (green-OK and yellow-defective)

Addressable function is activated by setting an ID on each luminaire with configuration tool (Cat.No 0 626 10) and wiring a complementary BUS line

Operating state of all addressable luminaires can be centralized by the control interface (Cat.No 0 626 00) and monitored on a local touch screen controller (Cat.No 0 626 01), or

with the building's plan on Legrand Vision System (LVS2) PC software Cat.No 0 626 02

These Maintained luminaires can also operate in Non-maintained mode according to the

wiring of normal lighting

100 lm - 3h (LEDs)

**Caracteristici generale**

B65 LED - weatherproof self-contained emergency lighting luminaire LED

Weatherproof LED maintained and non-maintained units

Certified to IEC and EN 60598-2-22 standards

High Putere LEDs. IP 65 - IK 07

Plug-in base to ease fixing, cabling and connection

Duration: 1 and 3 hours. Ni-Cd or Ni-MH batteries. Recharge time: 24 hours

Charge monitor with a green LED. Tensiune de alimentare: 230 V  $\pm$  10%- 50/60 Hz.

Class II

High-capacity screw terminals (2 x 2.5mm<sup>2</sup>)

3 flexible cable entries for O16, 20 and 25 mm tubes

Can be equipped with metallic protection grids Cat.Nos 0 626 90/92

Pret: 667,83 lei (TVA inclus)

Detalii online: <https://www.materialeelectrice.ro/lampa-de-emergenta-b65-autotest-address-maint-non-maint-100-lm-3h-led-225964>