

Furnizor: **Sc Trivolt Distribution SRL**
Reg. com.: J23/3300/2016
CIF: RO36421140
Adresa: Strada Apusului nr 3 (primul
sens giratoriu Tehodor Pallady-
Autostrada Soarelui), Catelu, Ilfov
Banca: BRD
IBAN: RO34BRDE441SV13182234410



IEK ARMAT SWICH CONTACT AR-AUX-DC 240...415V

The ARMAT AUX-DC change-over contact is used for status information of ARMAT M06N and M10N series circuit breakers in process automation or object-specific protection systems. It consists of two switching contacts: status contact (SC) and status/alarm contact (AUX-DC). The KS|KA contact operates, depending on the position of the function switch, either as a status contact or as an alarm contact. Attached without screws to M06N and M10N ARMAT circuit breakers. Device fitting: EV000028

Additional equipment: EV009833

Assembly width (TE): 9

Number of normally open contacts: 2

Number of normally closed contacts: 2

Number of change-over contacts: 0

Number of contacts as change-over contact: 0

Number of fault-signal switches: 4

Rated switch current: 6

Control voltage type: EV000460

Nominal rated voltage: 240...415

Nominal voltage DC: 24...130

Voltage type: EV000509

Compliance with current breakers: ARMAT

Conventional thermal current : 6

Construction type: EV008723

Operating temperature range: -5...40

Max. conductor cross section: 2,5

Width: 9.0

Height: 81.5

Depth: 75.6

Mounting method: EV000154

Mechanical wear resistance: 10000

Attachment Side to Authomatic current breaker: IEK_V0000367

Time off at min of actuation voltage: 0,01

Time off at max of actuation voltage: 0,01

Operation mode: IEK_V0000393

Wear resistance: 10000

Type of electric connection: EV000415

: 240...415

Pret: 0,00 lei (TVA inclus)

Detalii online: <https://www.materialelectrice.ro/armat-swich-contact-ar-aux-dc-240-415v-307314>