

LEGRAND 3-WIRE SENZOR DE MISCARE MOSAIC - CU NEUTRAL - IR DETECTION - 2000 W - ALU

Caracteristici tehnice
3-wire motion sensors, with neutral
IR detection - 2000 W
Checks the light level continuously and not only at the time of detection
Accepted Putere by lamp type :
LEDs: 0 to 250 W
Compact fluorescent: 0 to 250 W
LEDs, CFLs, Halogen, fluo tubes with ferromagnetic or electronic transformer: 0 to 1000 VA
Halogen 230 V, incandescent: 0 to 2000 W
Up to 10 sensors can be connected in parallel
Additional remote manual control possible with push button
Time delay setting from 5s to 30 min
Light level threshold setting from 5 lux to 1275 lux
Standby Consum : 0.2 W
Alu
Caracteristici generale
Mosaic™ Programme mechanisms - motion and presence sensors
All sensors are compatible with any lamp - Detection field: 120°
Detection range: 8 m
Recommended installation height: 1.20 m
Integrated self-protection against overloads and short-circuits.
2 module
Pret: 490,58 LEI (TVA inclus)

Detalii online: https://www.materialeelectrice.ro/3-wire-senzor-de-miscare-mosaic-cu-neutral-ir-detection-2000-w-alu-222297