www.MATERIALE ELECTRICE.ro
Consiliere specializata

LEGRAND* LAMPA DE EMERGENTA URA ONE - AUTOTEST & ADDRESSABLE M/NM - 1H - 100 LM - LED

Caracteristici tehnice
Autotest and addressable luminaires - Maintained/Non-maintained (M/NM)
Autotest/addressable luminaires incorporate an automatic self-testing system in order to check the emergency mode
Tests result is visible on 2 signalling LEDs (green-OK and yellow-defective)
Addressable function is activated by setting an ID on each luminaire with infrared configuration tool (Cat.No 0 626 10) and wiring a complementary BUS line
Operating state of all addressable luminaires can be centralized by the control interface (Cat.No 0 626 00) and monitored on a local touch screen controller (Cat.No 0 626 01), or with the building's plan on Legrand Vision System (LVS2) PC software (Cat.No 0 626 02)
These Maintained luminaires can also operate in Non-maintained mode according to the wiring of normal lighting
100 lm - 1h (LEDs)
Caracteristici generale
URA ONE - indoor self-contained emergency lighting luminaire LED
LED non-maintained and maintained units
Certified to IEC and EN 60598-2-22 standards
High Putere LEDs with optimized lighting distribution
Low Consum switching Tensiune de alimentare. Fully recyclable
Plug-in back with pre-cutted holes grid to ease installation and maintenance
Automatic terminals with high capacity: 2 x 2.5mm². IP 42 - IK 07
Duration: 1 and 3 hours. Ni-Cd or Ni-MH batteries. Recharge time: 24 hours. Charge monitor with a green LED. Opal diffuser
Tensiune de alimentare: 230 V~ ± 10% - 50/60 Hz. Class II
Flat Montaj incastrat integration into ceiling and wall with Montaj incastrat frame Cat.Nos 6 616 50/51
Decorative frame to enhance surface-mounting aesthetic integration Cat.Nos 6 616 54/55

Pret: 414,35 LEI (TVA inclus)

Detalii online: https://www.materialeelectrice.ro/lampa-de-emergenta-ura-one-autotest-addressable-m-nm-1h-100-lm-led-225985