

BTICINO INTRERUPATOR FARA FIR, 1 MODUL, PENTRU COMANDA UNUIA SAU MAI MULTOR DISPOZITIVE CONECTATE LIVING LIGHT WITH NETATMO

Descoper? Intrerup?tor fara fir, 1 modul, pentru comanda unuia sau mai multor dispozitive conectate Living Light with Netatmo din categoria Casa inteligenta - Gestiune si control, un produs cu codul LN4003CWI.
Acesta ofer? caracteristici excelente: Radio frequency 2400 MHz
Rolling code system Yes
Code length (Bit) 128
Range 185 m
Number of commands 1
With manual radio transmitter Yes
Flush-mounted radio transmitter Yes
Surface mounted radio transmitter No
With radio coding device Yes
Degree of protection (IP) IP40
Keyboard protection cover No
Current supply Battery
Width 22 mm
Height 47 mm
Depth 44.5 mm
Built-in depth 33.5 mm
Degree of impact strength (IK) IK04
Operating / setting temperature 5-45 °C
Storage temperature 0-45 °C
Standby consumption 0 mA
Mandatory neutral No
Stress test conformity (1000V) No
Colour Anthracite
RAL-number 7015

Halogen free Yes
Antimicrobial treatment No
Mounting method Flush-mounted
Contains Batteries and/or Accumulator Yes
IEC code (Pack1) CR2032
Battery ou Accumulator (Pack1) Battery (not rechargeable)
Element Composition (Pack1) Lithium (battery or accumulator)
Number of Pack 1 1
Number of Single Element (Pack1) 1
Single Element weight (Pack1) 3 g
Pack1 Location Product includes a battery
Regulation Type (Pack1) P : Portable (Standard format)
Connected object Yes
Operating method Zigbee
Application store for download Google Play Store , App Store
With voice command Yes
Programmable Yes
Interoperable connection Protocol Yes
Connectable by Internet box Yes
Compatible voice assistants Google Assistant , Amazon Alexa , Apple Siri
Product use function Lighting management
Application name Home + Control
Programming way Smartphone apps. Ideal pentru proiectele tale, asigurand eficien?? ?i calitate superioar?.
Pret: 249,91 LEI (TVA inclus)

Detalii online: https://www.materialeelectrice.ro/intrerupator-fara-fir-1-modul-pentru-comanda-unuia-sau-mai-multor-dispozitive-conectate-living-light-with-netatmo