



SCHNEIDER CONTACT AUXILIAR - 1 OC SAU 1 SD SAU 1 SDE SAU 1 SDV

Tip produs sau componenta: Contact auxiliar
nume scurt al dispozitivului: OF

SD

SDE

SDV

aplicatie a dispozitivului: Breaker status monitoring

Compatibilitate gama: Compact (ComPact NS630b...1600)

Compact (ComPact NS1600b...3200)

Compact (Compact INS)

Compact (Compact INV)

Compact (ComPact NSX)

Easypact (EasyPact CVS)

PowerPact (PowerPact Multistandard)

Compact (ComPact NSX DC)

compozitie contacte de semnalizare: 1 NO/NC

tip eroare: Defect electric general

semnalizare locala: Indicatie ON/OFF for open/close

Indicator declan?are for indicator declansare releu

Declansare defectiune for electrical fault

tip contacte auxiliare: Standard

mod de montare: Clipsabil

[I_{th}] curent termic conven?ional in aer liber: 5 A

Breaking capacity (A): AC-12: 6 A at 24 V c.a. 50/60 Hz

AC-12: 6 A at 48 V c.a. 50/60 Hz

AC-12: 6 A at 110 V c.a. 50/60 Hz

AC-12: 6 A at 220/240 V c.a. 50/60 Hz

AC-12: 6 A at 380/440 V c.a. 50/60 Hz

AC-12: 6 A at 480 V c.a. 50/60 Hz

AC-12: 6 A at 660/690 V c.a. 50/60 Hz

AC-15: 6 A at 24 V c.a. 50/60 Hz

AC-15: 6 A at 48 V c.a. 50/60 Hz

AC-15: 5 A at 110 V c.a. 50/60 Hz

AC-15: 4 A at 220/240 V c.a. 50/60 Hz

AC-15: 2 A at 380/440 V c.a. 50/60 Hz

AC-15: 1,5 A at 480 V c.a. 50/60 Hz

AC-15: 0,1 A at 660/690 V c.a. 50/60 Hz

DC-12: 6 A at 24 V c.c. 50/60 Hz

DC-12: 2,5 A at 48 V c.c. 50/60 Hz

DC-12: 0,6 A at 110 V c.c. 50/60 Hz

DC-12: 0,3 A at 250 V c.c. 50/60 Hz

DC-14: 1 A at 24 V c.c. 50/60 Hz

DC-14: 0,2 A at 48 V c.c.

DC-14: 0,05 A at 110 V c.c.

DC-14: 0,03 A at 250 V c.c.

sarcina minima: 100 mA la 24 V c.c.

terminal auxiliar de conectare: arc 0,5...1,5 mm² (AWG 20...AWG 16)

categoria accesorii/piese separate: Piese de schimb pentru Compact NS630b...1600

Piese de schimb pentru Compact NS1600b...3200

Pret: 125,17 LEI (TVA inclus)

Detalii online: <https://www.materialelectrice.ro/contact-auxiliar-1-oc-sau-1-sd-sau-1-sde-sau-1-sdv>