LEGRAND* LAMPA DE EMERGENTA URA ONE - STANDARD MAINTAINED/NON MAINTAINED - 3H - 100 LM - LED

Caracteristici tehnice
Standard luminaires
Require normal lightingmanual switching off in order test emergency lighting
Maintained/Non-maintained (M/NM)
Can also operate in Non-maintained mode according to the wiring of normal lighting
100 lm - 3h (LEDs)
Caracteristici generale
URA ONE - indoor self-contained emergency lighting luminaire LED
LED non-maintained and maintained units
Certified to IEC and EN 60598-2-22 standards
High Putere LEDs with optimized lighting distribution
Low Consum switching Tensiune de alimentare. Fully recyclable
Plug-in back with pre-cutted holes grid to ease installation and maintenance
Automatic terminals with high capacity: 2 x 2.5mm². IP 42 - IK 07
Duration: 1 and 3 hours. Ni-Cd or Ni-MH batteries. Recharge time: 24 hours. Charge monitor with a green LED. Opal diffuser
Tensiune de alimentare: 230 V~ ± 10% - 50/60 Hz. Class II
Flat Montaj incastrat integration into ceiling and wall with Montaj incastrat frame Cat.Nos 6 616 50/51
Decorative frame to enhance surface-mounting aesthetic integration Cat.Nos 6 616 54/55
Pret: 390,02 LEI (TVA inclus)

Detalii online: https://www.materialeelectrice.ro/lampa-de-emergenta-ura-one-standard-maintained-non-maintained-3h-100-lm-led-225993